

## PMA KS 98-2

### Multi-function Controller



## Automation made easy

PMA's multi-function instrument KS 98-2 combines PID control, process monitoring, sequence control, data logging and alarms.



- Modular automation system in a 1/4-DIN (96 x 96mm) format
- Measure, control, calculate, and record
- Process visualization, operation, alarm and alerts
- Comprehensive application-oriented functionality
- Graphical programming utility and simulator
- 3.5 " color touch-screen display
- USB interface on front fascia
- Expandable with modular inputs and outputs
- Ethernet and common fieldbuses

Function blocks from an extensive library can be used to build an application by easily selecting and connecting the blocks graphically using the "ET/KS98"-utility. This method is ideal for creating tailored control, including user interface pages with minimal effort. As a complete solution in a single unit, the KS 98-2 multi-function instrument helps to reduce programming, installation cost and control cabinet space.

## Hardware flexibility

- Unprecedented number of I/O in a 1/4-DIN device
- Fully adaptable with up to 12 internal I/O-modules
- Almost every 1/4 DIN Controller can be replaced/upgraded

KS 98-2 offers comprehensive modular input and output options to adapt the unit to the application needs. The unit is optimized to handle the precise measurements required in the process industry via I/O modules supporting a variety of sensor types and also have galvanic isolation. Additional signal conditioners and isolating amplifiers are not necessary in most applications, saving cost and less installation time.



## Easy creation of applications for simple and complex tasks

To program the multi-function instrument KS 98-2 for a specific application, the easy to use graphical engineering utility ET/KS98 is available. A variety of proven function blocks for control, sequencing and calculations can be easily selected and combined as needed for the application. A computer simulation helps to validate and improve the user program in the office before commissioning for live factory equipment.

By selecting functions from the library, the corresponding user screens for operation and setup are added to the user program automatically. Specific overview pages can be built and added to the application.



## Easy to maintain

- Via front accessible USB
- Via network access
- Using a USB flash drive



## Applications

- Multi loop control
- Sophisticated process control
- Profile control
- Complete automation of small applications

## Specifications

<b>Display</b>	320x240 Pixel Color TFT Display
<b>Operation</b>	Touch with dedicated virtual buttons below the viewing area
<b>Mechanics</b>	1/4-DIN panel mount Mounting depth 118mm
<b>IP rating</b>	IP65 (Front)
<b>Inputs</b>	Universal analog input and 2 digital inputs Modular expandable for various types of input signals (TC, RTD, mA, mV/V, 2-wire transmitters, zirconia probes, 24V logic) (Unit can support up to 12 dual channel I/O extension modules)
<b>Outputs</b>	2 or 4 Relays Modular expandable with various types of output signals (mA, V, SSR, 24V logic) (Unit can support up to 12 dual channel I/O extension modules)
<b>Communication</b>	Ethernet, USB, CAN. Optional modules for RS485, Profibus, Profinet
<b>Data Storage</b>	SD card
<b>Function Library and user program</b>	Logic, Math, Control, Profiling, Alarming, Recording, ... User program can combine up to 2000 function blocks and manage up to 30 control loops

## KS 98-2 Basic Unit

- Communication Options [D]**
- 0 None / for stand alone applications
  - 1 Standard interfaces (Ethernet/USB) and CAN for Remote I/O
  - 2 Standard interfaces plus RS485 / Modbus
  - 3 Standard interfaces plus Profibus
  - 4 Standard interfaces plus Profinet

- Base Models <sup>(1)</sup>**
- 0 Fast-on terminals
  - 1 Screw terminals

**KS98** - **2** **X** **X** - **X** **X** **X** **X** **X** - **X** **0** **0**

- Power Supply & Outputs [P]**
- 0 90...250V (2 relays, 2 option module slots)
  - 1 24V UC (2 relays, 2 option Slots)
  - 2 90...250V (4 relays)
  - 3 24V UC (4 relays)

- Options**
- 0 None
  - 1 Datalogger

- I/O Extensions [B]**
- 0 Not fitted
  - 1 Digital-I/O extension (10 DI, 4 DO)
  - 2 Modular extension (4 option module slots)

- Configuration**
- 0 Default settings; No option modules installed
  - 1 Default settings; Option modules according to additional order line
  - 8 Preset to specification; No option modules installed
  - 9 Preset to specification; Option modules according to additional order line

- Certification**
- 0 Standard (CE certified)
  - U UL / cUL certified
  - D DIN3440 / EN 14597

- I/O Extensions [C]**
- 0 Not fitted
  - 1 Digital-I/O extension (10 DI, 4 DO)
  - 2 Modular extension (4 option module slots)

(1) Universal Input, 2 digital Inputs, TPS, 2 option module slots

## Factory installed Option Modules

Into KS 98-2 in order line above

**A98** - **F** - **0** **0** **0** **0** **0** **0** **0** **0** **0** **0** **0** **0** **0** **0** **0**

*Factory installed*  
*Strip P / Segment 3*  
*Strip P / Segment 4*  
*Strip A / Segment 2*  
*Strip A / Segment 3*  
*Strip B / Segment 1*  
*Strip B / Segment 2*  
*Strip B / Segment 3*  
*Strip B / Segment 4*  
*Strip C / Segment 1*  
*Strip C / Segment 2*  
*Strip C / Segment 3*  
*Strip C / Segment 4*

**Modules and Positions**

0 0 0 0 0 0 0 0 0 0 0 0	Not fitted
- - U U U U U U U U U U	Universal input
- - R R R R R R R R R R	Dual Pt100/1000, Ni100/1000, resistance
- - T T T T T T T T T T	Dual Thermocouple, mV, 0/4...20mA
- - V V V V V V V V V V	Dual -50...1500mV (eg. Zirconia probe), 0...10V
- - P P P P P P P P P P	0/4...20mA Input with transmitter power supply
A A A A A A A A A A	Dual DC drive output for SSR
L L L L L L L L L L	Dual linear out (mA/V DC)
B B B B B B B B B B	Dual bipolar Linear Out (-10V...10V)
- - D D D D D D D D D D	Dual digital I/O

Please indicate for all option module slots (12 digits)

## Separate module orders

**A98** - **M** - **U**

- Available modules**
- U** Universal input
  - R** Dual Pt100/1000, Ni100/1000, resistance
  - T** Dual Thermocouple, mV, 0/4...20mA
  - V** Dual -50...1500mV (eg. Zirconia probe), 0...10V
  - P** 0/4...20mA Input with transmitter power supply
  - A** Dual DC drive output for SSR
  - L** Dual linear out (mA/V DC)
  - B** Dual bipolar Linear Out (-10V...10V)
  - D** Dual digital I/O

## Contact



**E-Mail:** [inquiries@west-cs.com](mailto:inquiries@west-cs.com)  
**Website:** [www.west-cs.com](http://www.west-cs.com)



**Address:** 1675 Delany Road  
Gurnee  
IL 60031  
USA



**Telephone:** +1 800 866 6659  
**Fax:** +1 847 782 5223